



The ME Series Inverter/Charger For Mobile Applications



The ME Series Inverter/Charger is powerful, easy-to-use, and cost effective.



The Powerful Difference

Reliable Mobile Power from Magnum Energy

Introducing the ME Series Inverter/Charger from Magnum Energy – a new generation inverter designed specifically for rugged mobile applications. The ME Series is powerful, easy-to-use, and best of all, cost effective.

Safe and reliable: The ME Series is ETL Listed to the stringent requirements of UL/cUL 458, ensuring that the inverter is safe and reliable.

Easy-to-install: Install the ME Series in four easy steps: simply connect the inverter's output to your distribution circuits or electrical panel, connect your shore power cable (AC) to the inverter's easy-to-reach terminal block, connect the batteries, and switch on the power.

Features

You asked and Magnum listened.

The ME Series Inverter/Charger is loaded with features:

Efficient: The **sine wave charger** efficiently charges your batteries even at low AC voltage, while the modified sine wave inverter keeps the cost down. Additionally, the battery temperature sensor works with the charger for optimum battery charging.

Choices: The ME Series comes in three power models, allowing you to choose the model that is right for you.

Upgradeable memory: The inverter is designed with Flash programming for easy memory upgrades.

Versatile mounting: Mount the ME Series on a shelf, bulkhead, or even upside down.

Lightweight: The lightweight aluminum base and cover also provides noise reduction and corrosion resistance.

Multiple ports: The ME Series provides multiple ports, including an RS485 communication port for network expansion, and a remote port.

Accessible design: The extra large AC access cover with terminal screw block and 360° DC connection terminals with covers make this inverter more accessible when it needs to be.

Convenient switches: The ME Series comes with an on/off inverter-mounted switch with an easy-to-read LED indicator.

Expanded transfer relay: 50 Amp transfer service is available on all models.

Buy with ease: The ME Series is backed by a three-year (36-month) limited warranty.

Accessories and Options*

Remote control: For convenient finger-tip operation, including the new one-knob™ programming.

AGS module: Automatically starts and stops your generator based on temperature or battery voltage.

** For more detailed information and specifications on these accessories, please see the accessories data sheet.*



The ME Series Inverter/Charger

Specifications

	ME2012	ME2512	ME3112
Inverter Specifications			
Input battery voltage	12.6 VDC	12.6 VDC	12.6 VDC
Nominal AC output voltage	120 VAC	120 VAC	120 VAC
Output frequency and accuracy	60 Hz ± 0.04%	60 Hz ± 0.04%	60 Hz ± 0.04%
1 msec surge current (amps AC)	60	100	120
100 msec surge current (amps AC)	37	45	50
5 sec surge power (real watts)	3700	5000	6000
30 sec surge power (real watts)	3450	4500	4800
5 min surge power (real watts)	3100	3500	3950
30 min surge power (real watts)	2400	2900	3500
Continuous power output at 45° C	2000 VA	2500 VA	3100 VA
Rated input battery current	191.0 ADC	239.1 ADC	296.5 ADC
Inverter efficiency	95%	91%	90%
Transfer time	16 msec	16 msec	16 msec
Search Mode (with remote)	.2 ADC	.2 ADC	.2 ADC
No Load (120 VAC output with remote)	0.87 ADC	0.95 ADC	0.97 ADC
Waveform	Modified Sine Wave	Modified Sine Wave	Modified Sine Wave

Charger Specifications

Continuous output at 45° C	100 ADC	120 ADC	160 ADC
Charger efficiency	85%	85%	85%
Power factor	0.98	0.98	0.98
Input current at rated output (AC amps)	15	18	21

General Features and Capabilities

Transfer relay capability	2 legs at 30 A for 120 V/30 A or 240 V/50 A service
Five stage charging capability	Bulk, Absorb, Float, Equalize, and Battery Saver™
Battery temperature compensation	With available temp sensor (battery temp 0 – 50° C)
Remote inverter on/off switch	With available pigtail to connect to dry contact
Internal cooling	0 to 120 cfm variable speed drive using dual 92mm brushless DC fans
Overcurrent protection	Yes, with two overlapping circuits
Overtemperature protection	Yes on transformer, MOSFETS, and battery
Conformal coating on PCB's for corrosion protection	Yes
Powder coated chassis & top for corrosion protection	Yes
Stainless steel fasteners for corrosion protection	Yes
Dual AC branch rated output breakers	Optional on the ME2012 - AC breakers in 15 or 20 amp ratings

Environmental Specifications

Operating temperature	-20° C to +60° C (-4° F to 140° F)
Nonoperating temperature	-40° C to +70° C (-40° F to 158° F)
Operating humidity	0 to 95% RH non condensing

Physical Specifications

Dimensions (h x w x d)	13.75" x 12.65" x 8.0" (34.9 cm x 32.1 cm x 20.3 cm)		
Mounting	Shelf (top or bottom up) or bulkhead (vents up)		
Weight	38 lb (17 kg)	42 lb (19 kg)	45 lb (20 kg)
Max operating altitude	15,000' (4570 m)		

Magnum Energy, Inc.

1111 80th Street SW, Suite 250
Everett, Washington 98203 USA

Phone: 425-353-8833
Fax: 425-353-8390
Web: www.magnumenergy.com

Testing for specifications at 25° C
Specifications subject to change without notice.
November 2004, Rev D

Authorized Magnum Dealer

The Powerful Difference